



DIIOOO

GreenPower series genserating sets, 3000 rpm, equipped with KOHLER diesel engines with electric starting system with key and battery. These generating sets are characterized by lower consumption and a longer life expectancy compared to the petrol powered range. 3000 rpm gensets have been designed for stand-by use only. Not recommended using for more than 6 hours continuously or more than 500 hours/year.



The image is only for demonstration purposes

PRIME POWER		STAND-BY POWER	
kVA	kW	kVA	kW
11	9,9	12,1	10,9

WEIGHT		DIMENSIONS	
kg	L [mm]	W [mm]	H [mm]
170	910	580	640



All data can be found out in the original technical datasheet of the engine and the alternator. Values shown are nominal values, they can change in every moment and without warning.



TECHNICAL DETAILS

ELECTRICAL DATA	Electrical system type	1F+N	~
	Power factor	0,9	φ
	Voltage	230	v
	Frequency	50	Hz
	Ampere rating	53,8	A
ENGINE DATA	Engine	KOHLER KD425	
	Engine emissions standards	STAGE V	
	Engine power	14,2 (10,5)	Hp (kW)
	Rpm	3000	
	Nr. of cylinders	2	
	Engine starting system	Electric starter	
	Displacement	851	сс
FUEL CONSUMPION DATA	Fuel type	Diesel	
	Consumption	2,8	lt/h @ 75%
	Tank capacity	4	lt
	Autonomy	1,4	h
ALTERNATOR DATA	Alternator	LINZ ELECTRIC – NSM	MADE IN ITALY
	Туре	Self-excited, brushless	
	Voltage regulation	Capacitor	
	Voltage precision	± 5	%



STANDARD EQUIPMENT



Steel base frame, epoxy powder painted



Anti-vibration dampers



First filling liquids



Electric starting with 12V battery



Electric manual panel: -n.1 230V EEC 16A 3P socket and n.1 230V EEC 32A 3P socket -General MCB, thermal switch, voltmeter and hour meter



OPTIONS



Automatic voltage regulator (AVR)



Slow trolley for manual handling



Bigger fuel tank for greater autonomy



Automatic mains failure panel -With integrated automatic transfer switch and battery charger

Greenpower AB

Helsingborgsvägen Varalöv, 262 96 Ängelholm, Sweden Phone: +46 43122240 Email: info@greenpower.se Web: www.greenpower.se